



Gate Repair Services

0114633025 0834522015

www.gates.co.za



G-SPEAK ULTRA)))

TECHNICAL SPECIFICATIONS

G-SPEAK ULTRA	
Supply Voltage Range	11-24V DC
Maximum Current Draw	300mA @ 12V DC
Input/output Current Rating	50mA (Open Collector)
Input Sense Voltage Range	0-24V DC (0-1.6V Low-input State, 5V-24V High-input State)
SIM Card	Micro-format, Activated Vodacom SIM Card Supplied ^{1,2}
Number of Configurable Input/output Channels	4
Call Buttons on Calling Module	2
Call confirmation at Calling Module	Yes
Speech volume	Adjustable at Calling Module using Call Buttons
Calling Module illumination	Call Buttons and labels with back-lit white LEDs
Memory Capacity	<ul style="list-style-type: none"> • 5000 Event logs • 20 Access Profiles • 1 Custom Welcoming SMS Message for New Access Numbers • 20 Custom Output Activation SMS Messages (From User to Device) • 30 Custom Input Notification SMS/Email Messages (From Device to User) • 100 Visitor Time-barring Windows (Windows are the periods between two dates) • 30 Generic Time-barring Windows (Windows are weekly recurring) • 10 Output Activation Schedules (Schedules are weekly recurring) • 3 Daylight Saving Periods • 4 Input to Output Mapping Configurations
GSM	Quad-band: GSM850, GSM900, DCS1800, PCS1900 GPRS Class 12

1. May not be used in devices other than **G-SPEAK ULTRA**.
2. Remains the property of Centurion Systems (Pty) Ltd.

For Gate Motor and Intercom Repairs, or Quotes on New Installations
Call the National Call Centre 011 463 3025 today
24 hour emergency 083 452 2015
repairs@gates.co.za / www.gates.co.za